

ECW100 INDOOR ACCESS POINT



INTRODUCTION

The ECW100 is a concurrent dual-band 802.11ac in-wall access point designed specifically for enhancing your traditional Ethernet/telephone outlets with Wi-Fi capabilities. It provides a Gigabit LAN port for your network devices and a pass-through telephone port for supporting telephone, modems and ADSL connections. Featuring two 2x2 MIMO radios, the ECW100 can simultaneously support up to 300 and 867 Mbps data rates in the 2.4 and 5 GHz bands respectively.

When the ECW100 is deployed and centrally managed by an Edgecore EWS Controller, additional value-added applications such as bandwidth control, user authentication, and captive portals can be used to provide an ideal solution for all types of businesses.

HIGHLIGHTS

WI-FI

- Concurrent Dual-Band 2.4 & 5 GHz
- 2x2 MIMO supporting up to
 1.2 Gbps data rate
- Support up to 16 ESSIDs.
- Enterprise-grade Wireless Security

PHYSICAL

- Simple Installation & Easy Per-room Deployment
- In-wall Design for US or EU standard outlets
- 802.3af PoE Uplink Port
- RJ-11 Pass-through Port

MANAGEMENT WITH EDGECORE WLAN CONTROLLER

- Captive Portal & Guest Provisioning
- Fast Layer 2 / Layer 3 roaming
- User-based Access Management
 - Bandwidth Control
 - Firewall Policies
 - Routing Policies
- Wi-Fi Monetization



- Suitable for US & EU-Standard Outlet Box
- RJ-11 Pass Through Compatible for Telephone Connections



www.edge-core.com

SPECIFICATIONS

PHYSICAL	
Power	PoE: 802.3af compliant (PoE injector optional)
Dimensions	+ US: 4.0 cm (L) x 7.0 cm (W) x 11.5 cm (H)
	+ EU: 4.0 cm (L) x 8.5 cm (W) x 8.5 cm (H)
Weight	+ 125 g (0.275 lbs)
	• Uplink: 1 x 10/100/1000Base-T Ethernet, Auto MDIX, RJ-45 with 802.3af PoE
Interfaces	 LAN: 1 x 10/100/1000Base-T Ethernet, Auto MDIX, RJ-45
	Bypass: 1 x RJ-11 (front) and 1 x RJ-11 (back)
	* Power
LED Indicators	1 x LAN Status (100 Mbps)
	1 x LAN Status (1 Gbps)
Buttons	Reset / Restart
Environmental Conditions	Operating Temperature: 0°C (32°F) to 40°C (104°F)
	Operating Humidity: 0% to 90% non-condensing
Power Consumption	* 8W max.
Antenna	 Type: 2 x Built-in (2 x 2.4 GHz, 2 x 5 GHz) Cui- 2 x Bi (2 4 GHz) 2 5 x Bi (5 GHz)
	Gain: 2 dBi (2.4 GHz), 3.5 dBi (5 GHz)
Mounting	In-Wall (Mounting plate included)
Tamperproof Mounting Kit Lock	
WI-FI	
Standards	 802.11 a/b/g/n/ac
	Concurrent dual-band 2.4 & 5 GHz
Supported Data Rates	* 802.11b: 1, 2, 5.5, 11 Mbps
	• 802.11a/g: 6, 9, 12, 18, 24, 36, 48, 54 Mbps
	 802.11n: 6.5 - 144 Mbps (20 MHz) 802.11n: 12.5 - 200 Mbps (40 MHz)
	 802.1111.13.5 - 300 MDpS (40 MHz) 802.11ac: 6.5 - 172.4 Mbps (20 MHz)
	* $802.11ac: 0.5 = 175.4 Mbps (20 MHz)$
	 802.11ac. 19.3 – 400 MBp3 (40 MHz) 802.11ac. 29.3 – 866.6 Mbps (80 MHz)
Radio Chains	+ 2 x 2
Spatial Streams	* 2
Spatial Streams	• 24 GHz: Up to 10 dBm* ²
RF Output Power*1	 5 GHz: Up to 10 dBm^{*2}
Channelization	* 20 MHz
	* 40 MHz
	* 80 MHz
	• 2.412 – 2.472 GHz
Frequency Band	• 5.180 – 5.825 GHz
Operating Channels	• 2.4 GHz: 1 – 11 (US), 1 – 13 (Europe), 1 – 13 (Japan)
	 5 GHz*³: 36 – 165 (US), 36 – 140 (Europe), 36 – 140 (Japan)
ESSIDs	• Up to 8 per radio (16 total)
PERFORMANCE	
Physical Data Data	• Up to 300 Mbps (2.4 GHz)
	+ Up to 867 Mbps (5 GHz)
Concurrent Users	• Up to 200 (100 on 2.4 GHz, 100 on 5 GHz)

*1: RF output power doesn't contain antenna gain*2: Maximum power is limited by local regulatory requirements*3: Some channels are restricted by local regulatory requirements

CONCURRENT DUAL-BAND 11AC IN-WALL ECW100

www.edge-core.com

QUALITY OF SERVICI	
Wireless QoS (802.11e/V	/MM)
DSCP (802.1p)	
Multicast to Unicast Cor	iversion
Optimal Client Filtering	
MANAGEMENT	
	 Standalone
Deployment	 Tunneled management by

Deployment	Edgecore EWS Controller
	 IPv4 compatible
	 Web User Interface (HTTP/
Configuration	HTTPS)
	 SNMP v1, v2c, v3

SECURITY	
Wireless Security	 WEP WPA/WPA2 Mixed (TKIP/AES Mixed) WPA2-Personal (AES) WPA2-Enterprise (AES)
VLAN Tagging (802	.1Q)
Station Isolation	
DHCP Snooping	
Layer-2 Firewall	

MOBILITY/ROAMING

802.1X Preauthentication Layer 2/Layer 3 Fast Roaming

VE SENSITIVITY		
Operating Mode	Data Rate	Receive Sensitivity (dBm
802.11b	1 Mbps	-91
	11 Mbps	-84
802 112	6 Mbps	-86
802.118	54 Mbps	-69
000 11 -	6 Mbps	-86
802.11g	54 Mbps	-69
	MCS0	-85
	MCS7	-68
802.11h (H120)	MCS8	-85
	MCS15	-66
	MCS0	-84
	MCS7	-65
802.11h (H140)	MCS8	-84
	MSC15	-63
	MCS0	-85
802.11ac (VH120)	MCS8	-65
802 11 ac (V/HT40)	MCS0	-84
502.11ac (VIII40)	MCS9	-60
802 11ac (V/HT80)	MCS0	-80
002.11dc (V1100)	MCS9	-54

SIGNAL COVERAGE PATTERN



TEL: 886-3-5638888 FAX: 886-3-6686111 1, Creation Rd. III, Hsinchu Science Park, Taiwan 30077 sales@edge-core.com www.edge-core.com

© Copyright 2019 Edgecore Networks Corporation. The information contained herein is subject to change without notice. This document is for informational purposes only and does not set forth any warranty, expressed or implied, concerning any equipment, equipment feature, or service offered by Edgecore Networks Corporation. Edgecore Networks Corporation shall not be liable for technical or editorial errors or omissions contained herein.